## Polebox 205 ED



Mounting and installation products E-mobility EV-charger pole mount NEXT GREEN – POLEBOX 205 ED

	Model
<b>E-No:</b> 27 001 77 <b>S-No:</b> 35 063 10	<b>Product name:</b> Charging box mount Polebox 205 ED



## **Technical specifications**

Material Color

Dimensions
Weight
Height
Width
Depth
Mounting surface

9 kg
600 mm
400 mm
450 mm

Steel, High-strength steel, Magnelis® Graphite grey

**Next Green Polebox 205 ED** is a tube or pole mount for EVcharging boxes for mounting on a 60 mm steel tube or pole. Polebox makes it easy, for example when changing from engine heater location to charging location and can therefore be used to replace an engine heater hood. The product is intended for feeding electrical cables inside the tube or pole.


9 kg 592 mm 367 mm 437 mm 205 mm

Polebox has a built-in distribution terminal for up to 2 x 5G25 mm2 power cable for extending the connection to the next charging post. From the distribution terminal in the Polebox, the respective charging box is then connected using a 5G2.5 mm2 rubber cable.

Polebox comes with a DIN rail to mount RCCB/RCBO and can be equipped with an additional DIN rail for units such as a Wi-Firouter or a 3G/4G modem or power supply.

## **POLEBOX 205 ED FEATURES**

- For mounting on Ø 60 mm steel tubes
- Most of the installation can be prepared indoors
- Robust steel construction
- Distribution block has support for 1.5 mm2 - 25 mm2 cable, Al and Cu
- Prepared for mounting an RCCB/RCBO, 3G / 4G router
- Powder coated, available in various colors. Contact Next Green for more information



Everything fits neatly inside the box. Polebox is made of Swedish steel and powder coated to provide the highest quality. Polebox is made to fit many different charger models. Mounting holes for each charger are drilled upon installation. Polebox is very easy to install. It is prepared indoors by mounting the EV-chargers and installing the wiring from the distribution terminal. Polebox is then put in place outside on the existing steel tube and the charger hood is lifted and fastened. This provides easy to access for screwing supply wires into the distribution terminal.

## next 🚽 green

Next Green AB Brudtallsvägen 14 SE-792 32 MORA SWEDEN www.nextgreen.se info@nextgreen.se Tel: +46 250 50 39 90